



**genesis**<sup>™</sup>  
XE  
PURELEAD  
**RANGE SUMMARY**

The Genesis<sup>™</sup> XE thin plate pure lead battery excels in demanding environmental and cycling applications such as:

- Alternative energy applications, e.g. solar and wind power
- Hybrid electric vehicles (HEV)







### Specifications

#### Battery Design

- 12V pure lead-tin VRLA AGM battery
- UL94 V-0 flame retardant case and cover
- M6 female no-maintenance terminals, 3/8-16 female terminals for XE95
- Can be installed in any orientation except inverted
- Rugged construction (optional metal jacket, except for XE60 and XE95)
- Approved for shipping as non-hazardous, nonspillable

#### Performance Features

- -40°C to 80°C (-40°F to 176°F) with metal jacket
- 300+ full depth of discharge cycles
- High rate charge and discharge
- 2 year shelf life at 25°C (77°F)
- Superior deep discharge recovery
- UL recognized - file No. MH12544



## General Specifications

Type	Nominal Voltage (V)	Nominal Capacity (Ah)	Nominal Dimensions						Overall Weight		Torque		Internal Resistance (mΩ)	Typical Short Circuit Current (A)
		10 hr rate to 1.67Vpc @ 25°C/77°F	Length mm	in	Width mm	in	Height mm	in	kg	lbs	in-lbs	Nm		
XE13	12	13	175.0	6.89	83.1	3.27	129.0	5.08	5.4	11.9	50	5.6	9.0	1400
XE16	12	16	180.8	7.12	75.9	2.99	166.9	6.57	6.4	14.1	50	5.6	7.5	1600
XE30	12	28	165.9	6.53	175.0	6.89	125.0	4.92	10.2	23.3	60	6.8	5.0	2400
XE40	12	42	196.6	7.74	165.1	6.50	169.9	6.69	16.1	35.4	60	6.8	4.5	2600
XE60	12	62	275.6	10.85	171.7	6.76	180.8	7.12	22.4	49.4	60	6.8	2.5	3100
XE70	12	68	328.7	12.94	166.1	6.54	174.0	6.85	25.7	56.6	60	6.8	3.5	3500
XE95	12	95	329.9	12.99	172.5	6.79	218.9	8.62	35.1	77.4	60	6.8	2.2	5000

## Constant Current Discharge Performance

Constant current discharge rate, amps to 10.02V at 25°C (77°F)

Battery	Minutes				Hours					
	5	10	15	30	1	5	8	10	20	
XE13	64.4	39.6	29.2	16.9	9.6	2.3	1.5	1.2	0.7	
XE16	78.8	49.3	36.7	21.6	12.3	3.0	2.0	1.6	0.8	
XE30	142.8	90.6	67.4	39.2	21.9	5.2	3.4	2.7	1.5	
XE40	199.1	127.9	96.0	56.6	32.1	7.7	5.0	4.1	2.2	
XE60	304.4	193.6	144.5	84.2	47.3	11.5	7.6	6.2	3.4	
XE70	337.6	218.5	163.8	96.0	53.6	12.4	8.0	6.5	3.4	
XE95	449.5	290.7	219.5	129.5	73.5	17.8	11.7	9.6	5.2	

## Constant Power Discharge Performance

Constant power discharge rate, watts per battery to 10.02V at 25°C (77°F)

Battery	Minutes				Hours					
	5	10	15	30	1	5	8	10	20	
XE13	701.0	443.0	330.0	195.0	111.0	27.0	17.0	14.0	7.0	
XE16	857.0	546.0	412.0	247.0	143.0	36.0	24.0	19.0	10.0	
XE30	1565.0	1017.0	767.0	455.0	258.0	62.0	41.0	33.0	18.0	
XE40	2155.0	1426.0	1085.0	652.0	376.0	93.0	60.0	49.0	26.0	
XE60	3337.2	2175.4	1644.2	976.8	556.3	137.1	90.3	74.2	40.7	
XE70	3636.0	2411.0	1833.0	1091.0	615.0	142.0	90.0	73.0	37.0	
XE95	4883.4	3241.8	2482.0	1494.0	861.6	212.4	139.8	114.0	61.2	

## Charge Voltage

**Cyclic use:** 14.7V to 15.0V at 25°C (77°F) No current limit

**Float use:** 13.5V to 13.8V at 25°C (77°F) No current limit



www.enersys.com

**EnerSys**  
P.O. Box 14145  
Reading, PA 19612-4145  
USA  
Tel: +1-610-208-1991  
+1-800-538-3627  
Fax: +1-610-372-8613

**EnerSys EMEA**  
Brussels, Belgium  
Tel: +32 (0)2 247 94 47

**EnerSys Asia**  
Guangdong, China  
Tel: +86-755-2689 3639

Distributed by:

1573 Laperriere Ave. Ottawa ON K1Z 7T3  
(613) 725-3704 www.cantecsystems.com



Printed in USA  
© 2006 EnerSys. All rights reserved.  
Trademarks and logos are the property of EnerSys and its affiliates unless otherwise noted.